

IC Realtime Camera		ICIP D1300VIR	
Description		Network Dome Camera	
Number of documented streams:	2	Documented Simultaneous Streams:	20

TSX

MJPEG

Supported:	Yes		
Resolution:	1280x720	Camera Quality Setting:	bit rate 2048
Frames per second (fps):	10	Switching Time:	1~8
URL with user name and password: http://<IP address>/axis-cgi/mjpg/video.cgi?camera=0??user=<>&pw=<>			
URL without username and password http://<IP address>/axis-cgi/mjpg/video.cgi?camera=0?			
URL Example http://172.30.46.145/axis-cgi/mjpg/video.cgi?camera=0?			

H.264

Supported	Yes		
Resolution:	D1 (704x480)	Max Bandwidth	1024K bps
Frames per second (fps):	8	Switching Time	1~4 s
I-Frame Setting	1 per 10 frames		
URL with user name password: rtsp://<username>:<password>@<IP address>:<port>			
URL without user name password: rtsp://<IP address>:<port>			
URL Multicast: -			
URL Example rtsp://admin:admin@192.168.1.45:554			

TPMC-V12/15, DGE-2. TPMC-8X-GA**MJPEG**

Supported:	Yes		
Resolution:	1280x720	Camera Quality Setting:	Good
Frames per second (fps):	15	Switching Time:	1-2 secs
URL with user name and password:			
http://<username>:<password>@<IP address>:80/axis-cgi/mjpg/video.cgi?camera=0			
URL without username and password			
N/A			
URL Example			
http://admin:admin@172.30.176.119:80/axis-cgi/mjpg/video.cgi?camera=0			

H.264

Supported	Yes		
Resolution:	1280x720	Max Bandwidth	15
Frames per second (fps):	Good	Switching Time	1-2 secs
I-Frame Setting	N/a		
URL with user name password:			
rtsp://<username>:<password>@<IP address>:<port>/live			
URL without user name password:			
N/A			
URL Multicast:			
-			
URL Example			
rtsp://admin:admin@172.30.176.119<port>/live			

TPMC-4SM

MJPEG

Supported:	Yes		
Resolution:	740x480	Camera Quality Setting:	bit rate 1024
Frames per second (fps):	5	Switching Time:	1 ~ 8
URL with user name and password: http://<IP address>/axis-cgi/mjpg/video.cgi?camera=0??user=<>&pw=<>			
URL without username and password -			
URL Example -			

H.264

Supported	No		
Resolution:	N/A	Max Bandwidth	N/A
Frames per second (fps):	N/A	Switching Time	N/A
I-Frame Setting	N/A		
URL with user name password: N/A			
URL without user name password: -			
URL Multicast: -			
URL Example -			

Crestron App

MJPEG

Supported:	Yes		
Resolution:	1280x720	Camera Quality Setting:	Good
Frames per second (fps):	5	Switching Time:	2-4 sec
URL with user name and password:			
http://<username>:<password>@<IP address>:80/axis-cgi/mjpg/video.cgi?camera=0			
URL without username and password			
N/A			
URL Example			
http://admin:admin@172.30.176.119:80/axis-cgi/mjpg/video.cgi?camera=0			

H.264

Supported	No		
Resolution:	-	Max Bandwidth	
Frames per second (fps):		Switching Time	
I-Frame Setting			
URL with user name password:			
N/A			
URL without user name password:			
N/A			
URL Multicast:			
N/A			
URL Example			
N/A			