Dual AM/FM Radio Tuner Card

The ATC-AMFM2 tuner card is designed for use with the Crestron CEN-TRACK TunerRack Modular Multi-Tuner, and with Adagio® systems that features tuner card slots. The ATC-AMFM2 provides two (2) fully independent AM/FM tuners on a single card.

SPECIFICATIONS

Audio

Maximum Output: 1 Vrms @ 1kHz

FM Tuner (Typical of 2)

Frequency Range: 87.50 to 108 MHz (50 or 100 kHz steps)

Usable Sensitivity: 11 dBf mono;

60 dBf stereo

S/N Ratio: 64 dB @ 65 dBf mono;

56 dB @ 65 dBf stereo IF Rejection: 100 dB AM Rejection: 55 dB Stereo Separation: 27 dB

AM Tuner (Typical of 2)

Frequency Range: 530 to 1710 kHz (9 or 10 kHz steps)

Sensitivity: $3.5 \mu V$ (RF input level 10 dB S+N/N)

Selectivity: 10 kHz

Alternate Channel Selectivity: 55 dB

Image Rejection: 35 dB IF Rejection: 60 dB

Connectors

FM ANT (A – B): (2) IEC 169-2 coaxial (IEC-to-F adapters included);

(2) FM wire antennas included:

Impedance: 75 Ohms

AM ANT (A - B): (2) 2-pin spring-loaded terminals;

(2) AM shielded loop antennas included;

Impedance: 50 Ohms

Weight

9.84 oz (279 g)



MODELS & ACCESSORIES

Available Models

ATC-AMFM2: Dual AM/FM Radio Tuner Card

Notes:

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

Specifications subject to change without notice. Crestron is not responsible for errors in typography or photography.

Crestron, Adagio, and the Crestron logo are trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and other countries. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others.

©2011 Crestron Electronics, Inc.

ATC-AMFM2 Dual AM/FM Radio Tuner Card







