

Vivotek	FD8134V (720)		
Description	Fixed Dome Network Camera		
Number of documented streams:	4	Documented Simultaneous Streams:	10

TSX

MJPEG

Supported:	Yes		
Resolution:	(320x200)	Camera Quality Setting:	good
Frames per second (fps):	15	Switching Time:	1 ~ 10 depends on the camera server and load.
URL with user name and password:			
http://<IP address>/video.mjpg?user=<username>&pw=<password>			
URL without username and password			
http://<IP address>/video.mjpg			
URL Example			
http://192.168.70.45/video.mjpg?user=admin&pw=admin			

H.264

Supported	Yes		
Resolution:	1280x720	Max Bandwidth	1 Mb/s
Frames per second (fps):	15	Switching Time	1 ~ 10 depends on the camera server and load.
I-Frame Setting	1/s		
URL with user name password:			
rtsp://<username>:<password>@<IP address>/live.sdp			
URL without user name password:			
rtsp://<IP address>/live.sdp			
URL Multicast:			
http://<IP address>/live.sdp			
URL Example			
rtsp://admin:admin@192.168.1.112/live.sdp			

TPMC-V12/15, DGE-2. TPMC-8X-GA**MJPEG**

Supported:	Yes		
Resolution:	640x400	Camera Quality Setting:	Good
Frames per second (fps):	15	Switching Time:	1-2 secs
URL with user name and password:			
http://[<username>:<password>@]<IP address>:<port>/<[video.mjpeg video2.mjpg video3.mjpg video4.mjpg]>			
URL without username and password			
http://<IP address>:80/video.mjpg			
URL Example			
http://root.root@172.30.176.228:80/video.mjpg			

H.264

Supported	Yes		
Resolution:	1280x720	Max Bandwidth	Constant bit rate: 3 Mbps
Frames per second (fps):	15	Switching Time	1-4 secs
I-Frame Setting	1/4 S		
URL with user name password:			
rtsp://[<username>:<password>@]<IP address>:<port>/<[live1.sdp live2.sdp live3.sdp live4.sdp]>			
URL without user name password:			
rtsp://<IP address>:554/live.sdp			
URL Multicast:			
Yes			
URL Example			
rtsp://root.root@172.30.176.228:554/live.sdp			

TPMC-4SM**MJPEG**

Supported:	Yes		
Resolution:	320x200	Camera Quality Setting:	good
Frames per second (fps):	15	Switching Time:	1 ~ 10 depends on the camera server and load.
URL with user name and password:			
http://<IP address>?user=<username>&pw=<password>			
URL without username and password			
-			
URL Example			
-			

H.264

Supported	Yes		
Resolution:	320x200	Max Bandwidth	128Kbps
Frames per second (fps):	15	Switching Time	1 ~ 10 depends on the camera server and load.
I-Frame Setting	1/s		
URL with user name password:			
rtsp://<username>:<password>@<IP address>			
URL without user name password:			
-			
URL Multicast:			
-			
URL Example			
-			

Crestron App**MJPEG**

Supported:	Yes		
Resolution:	1280x720	Camera Quality Setting:	Standard
Frames per second (fps):	5	Switching Time:	2-4 sec
URL with user name and password:			
http://root.root@172.30.176.228:80/video.mjpg			
URL without username and password			
http://root.root@172.30.176.228:80/video.mjpg			
URL Example			
http://root.root@172.30.176.228:80/video.mjpg			

H.264

Supported	No		
Resolution:	N/A	Max Bandwidth	N/A
Frames per second (fps):	N/A	Switching Time	N/A
I-Frame Setting	N/A		
URL with user name password:			
N/A			
URL without user name password:			
N/A			
URL Multicast:			
N/A			
URL Example			
N/A			