

IC-200-P PAK

IntelliClass™ Classroom AV System Package

Crestron® IntelliClass™ systems provide educators with a simplified yet comprehensive classroom presentation solution that saves time and money. Designed to deliver the highest level of quality and convenience without using up the AV/IT budget, IntelliClass assembles all the vital pieces needed to outfit classrooms for an engaging teaching experience.

IntelliClass makes it easy and affordable to install a quality projection system in every classroom, ending the days of wheeling in the AV cart or forcing students to squint at a tiny TV screen. The IC-200-P package includes a professional wall mount controller, high-performance speakers and amplifier, universal ceiling projector mount, multimedia input wall plates, cabling, and connectors. Just add a preferred video projector and screen to complete the classroom presentation system. IntelliClass also integrates seamlessly with interactive whiteboards and wireless microphones.


The diagram to the right shows a typical IC-200-P system arrangement.

1 Verify Contents

Before starting installation procedures, check the contents of the system package. The following table lists the items that should have been received. Retain all documents and parts supplied for use in the installation process.

| DESCRIPTION | PART NUMBER | QTY |
|---|--------------------------------------|-----|
| Media Presentation Controller, White | MPC-M5-W | 1 |
| Media Presentation Audio Amplifier | MP-AMP30 | 1 |
| Surface Mount Media Presentation Speakers, Pair, White | FS6-W | 1 |
| Media Presentation Wall Plate, Video and Audio, White | MP-WP100-W ¹ | 1 |
| Media Presentation Wall Plate, VGA and Audio, White | MP-WP131-W ¹ | 1 |
| Universal Ceiling Projector Mount, White | PMTC-50-6W | 1 |
| Power Pack for MP-AMP30 | PW-2420RU | 1 |
| PoE Injector for MPC-M5 | PWE-4803RU | 1 |
| RS-232 Projector Control Cable, Plenum, 50 ft (15 m) | CBL-KSERIAL-DB9-L-P-50 ² | 1 |
| Ethernet LAN Cable, Plenum, 50 ft (15 m) | CBL-CAT5E-P-50 ² | 1 |
| Speaker Cable, 16 AWG, Plenum, 35 ft (11 m) | CBL-SPK-P-35 | 2 |
| RCA Video and Stereo Audio Cable, Plenum, 50 ft (15 m) | CBL-KAV-RCAM3-L-P-50 ^{2,3} | 1 |
| HD15 VGA Cable, Plenum, 50 ft (15 m) | CBL-KVGA-L-P-50 ^{2,3} | 1 |
| RCA Stereo Audio Cable, Plenum, 50 ft (15 m) | CBL-KAUDIO-RCAM2-L-P-50 ² | 1 |
| Projector-to-Amplifier RCA Stereo Audio Cable, 3 ft (1 m) | (Supplied with MP-AMP30) | 1 |
| RCA to 3.5 mm Mini-TRS Stereo Audio Adapter | CBL-AUDIO-RCAF-0.5 ² | 3 |
| 1-Gang Low-Voltage Trim Ring | BB-G1-LV | 2 |
| 2-Gang Low-Voltage Trim Ring | BB-G2-LV | 1 |

1. Each package includes a 2-gang post-construction trim ring for the MPC-M5-W and a 1-gang post-construction trim ring for each wall plate.
 2. Specified in illustration on page 2.
 3. Includes uninstalled RCA and/or BNC compression connectors as required for termination at the wall plate. Installation requires IDEAL OmniSeal™ 30-793 or equivalent compression tool (not included).




*These cables are sold separately.

Tools Required (Not Supplied)

- Hand-held drill
- Wire cutter
- Wire stripper
- Phillips screwdriver(s)
- Flatblade screwdriver(s)
- Compression tool for supplied RCA and BNC connectors (Refer to footnote 3 in the table on this page.)

2 Installation

- Refer to the documentation supplied with the projector to determine the optimum mounting location. Refer also to the typical hookup arrangement diagram provided in section 3 on page 2.
- Install the PMTC-50-6W Universal Ceiling Projector Mount following the instructions contained in the installation guide (Doc. 7013), supplied.
- Mount the MP-AMP30 Media Presentation Audio Amplifier to the PMTC-50-6W (using four screws, eight washers, and four wingnuts provided). Refer to the diagram to the right for details.
- Mount the FS6-W speakers to the walls following the instructions contained in the quickstart guide (Doc. 6972), supplied.
- Mount the Media Presentation Wall Plate devices in appropriate locations in the room. Install appropriate faceplates (not supplied).
- Run the cables for the system. The supplied cables are plenum rated so they can be routed above the ceiling and are already terminated for the projector end. The opposite ends are not terminated to make it easier to route the cables through the walls and ceiling.
- Terminate BNC and RCA fittings as required.
- Configure the MPC-M5 Media Presentation Controller using the MPC Wizard in SystemBuilder™, which can be obtained at www.crestron.com/systembuilder.



IC-200-P PAK

IntelliClass™ Classroom AV System Package

3 Typical Hookup Arrangement

